

Problem B

Black Box

Time Limit: 1.0 Seconds

The following **Python**-like pseudo code for function **BlackBox()** takes a list of positive integers and shuffles the integers in the list in a specific way, and returns the result as a list.

Three list methods are used below; For a list L , $\text{len}(L)$ returns the number of items in L . $L.\text{append}(x)$ adds the item x to the end of L . $L.\text{pop}(\text{idx})$ removes the item at the specified index idx from the list L and returns the removed item.

Given a list **Z** of positive integers, write a program to reconstruct a list **I** such that **Z = BlackBox(I)**.

```
function BlackBox( Banana ) :
    if len( Banana ) <= 4 :
        exit("Too small Banana")
    Apple = [] # [] is an empty list
    Mango = 0
    Papaya = len( Banana )

    while( Papaya >= 2 ) :
        Kiwi = Banana[ Mango ]
        Apple.append( Kiwi )
        Banana.pop( Mango )
        Papaya = Papaya - 1
        Mango = ( Kiwi + Mango - 1 ) % Papaya
    # end of while

    Apple.append( Banana[ 0 ] )
    Pear = len( Apple ) - 1
    Orange = Apple[ Pear ]
    Lime = Apple[ 0 ]
    Coconut = Orange % Pear
    Melon = Apple[ Coconut ]
    Apple[ 0 ] = Melon
    Apple[ Coconut ] = Lime

    return ( Apple )
# end of function BlackBox
```

Input

Your program is to read from standard input. The first line contains a positive integer n representing the number of positive integers of a list \mathbf{Z} , where $5 \leq n \leq 200,000$. The following n lines contain n positive integers of the list \mathbf{Z} returned from **BlackBox**(\mathbf{I}); the i -th line contains the i -th integer of the list \mathbf{Z} between 1 and 100,000, both inclusive.

Output

Your program is to write to standard output. Print n integers of the list \mathbf{I} where $\mathbf{Z} = \mathbf{BlackBox}(\mathbf{I})$, one per line; the i -th line should contain the i -th integer of \mathbf{I} .

The following shows sample input and output for two test cases.

Sample Input 1

13
113
49
68
91
10
179
2
71
78
45
57
10
88

Output for the Sample Input 1

10
113
179
68
57
45
10
2
88
71
49
78
91

Sample Input 2

9
6
8
7
9
5
1
2
4
3

Output for the Sample Input 2

9
8
7
6
5
1
2
3
4