H Controllers



Time limit: 2.0s Memory limit: 2048MB

You are at your grandparents' house and you are playing an old video game on a strange console. Your controller has only two buttons and each button has a number written on it.

Initially, your score is 0. The game is composed of n rounds. For each $1 \le i \le n$, the i-th round works as follows.

On the screen, a symbol s_i appears, which is either + (plus) or - (minus). Then you must press one of the two buttons on the controller **once**. Suppose you press a button with the number x written on it: your score will increase by x if the symbol was + and will decrease by x if the symbol was -. After you press the button, the round ends.

After you have played all n rounds, you win if your score is 0.

Over the years, your grandparents bought many different controllers, so you have q of them. The two buttons on the j-th controller have the numbers a_j and b_j written on them. For each controller, you must compute whether you can win the game playing with that controller.

INPUT

The first line contains a single integer n $(1 \le n \le 2 \cdot 10^5)$ — the number of rounds.

The second line contains a string s of length n — where s_i is the symbol that will appear on the screen in the i-th round. It is guaranteed that s contains only the characters + and -.

The third line contains an integer q $(1 \le q \le 10^5)$ — the number of controllers.

The following q lines contain two integers a_j and b_j each $(1 \le a_j, b_j \le 10^9)$ — the numbers on the buttons of controller j.

OUTPUT

Output q lines. On line j print YES if the game is winnable using controller j, otherwise print NO.

SAMPLES

Sample input 1	Sample output 1
8	YES
+-++-	NO
5	NO
2 1	NO
10 3	YES
7 9	
10 10	
5 3	

Explanation of sample 1.

One possible way to get score 0 using the first controller is by pressing the button with number 1 in rounds 1, 2, 4, 5, 6 and 8, and pressing the button with number 2 in rounds 3 and 7. It is possible to show that there is no way to get a score of 0 using the second controller.

Sample input 2	Sample output 2
6	YES
+-++	YES
2	
9 7	
1 1	

Sample input 3	Sample output 3
20	NO
++-	YES
2	
1000000000 99999997	
250000000 1000000000	